



Description

XA 2309 splitter is designed for branching or two-way asymmetric splitting of radio signal. It works in broad frequency range. IN and OUT ports can be interchanged.

Technical Specifications

Parameter		Value	Units
Frequency range		0 ÷ 1860	MHz
Insertion loss		max. 0.35	dB
Coupling	+15 ÷ +35 °C	40,0 (+1.0 ÷ -1.8)	dB
	-25 ÷ +55 °C	40,0 (+1.4 ÷ -2.2)	dB
VSWR		< 1.4	
Maximum input power	continual operation CW	20	W
Impedance		50	Ω
Dimensions w × h × d		92 × 80 × 30	mm
Weight		0.185	kg
Connectors type	IN, OUT	N female, N male	
	CPL	BNC female	